

# energenie

GREEN ENERGY FOR OUR PLANET



EG-PM1W-001 WIFI SMART HOME SOCKET

USER MANUAL  
HANDBUCH  
HANDLEIDING  
MANUEL DESCRIPTIF  
РУКОВОДСТВО ПОЛЬЗОВАТЕЛЯ  
КЕРІВНИЦТВО КОРИСТУВАЧА

**WIFI smart home socket**  
**Programmierbare Smart Home WLAN**

**Steckdose**

**WIFI Smarthome Socket**

**WiFi prise de courant de la maison**  
**intelligente**

**WiFi розетка для умного дома**

**Wi-Fi розетка для розумного будинку**



- Do not plug several sockets in line
- Do not use if covered
- De-energized only if power plug is unplugged
- **NEVER** connect appliances which do not allow unattended operation!



## 1. Introduction

Thank you for your purchase of this EnerGenie *WiFi smart home socket*. Your EG-PM1W-001 is an advanced power socket with smart power management features. You can control the socket via your local WiFi network, the internet, or the PowerMan app.

Because you can control the smart socket via several different interfaces (power manager interface with secure data transfer, embedded webserver and [energenie.com](http://energenie.com) cloud service), it can be integrated into most smart home solutions.

With your free personal user account at our [EnerGenie.com](http://EnerGenie.com) cloud server, you can manage your EG-PM1W-001 from all over the world with any internet browser. With your free user account, you also get access to our free PowerMan app for controlling the EG-PM1W-001 (available for iOS and Android smartphone or tablets).

The EG-PM1W-001 also has a WiFi repeater function, which enables it to extend the range of your home or office WiFi network.

The smart socket can be switched on/off manually, via a timer schedule, or by different programmable events. The timer schedule is stored inside the device itself (hardware schedule only), so the smart socket does not need any network connection to execute the timer schedule.

## 1.1. Features

- Intelligent programmable WiFi power socket with built-in WiFi-repeater function
- Switch connected devices on or off with your computer, tablet or smart phone
- Fully featured programmable timer schedule possibilities
- Link on/off switching of the socket to certain software events or Windows start-up/shutdown
- Easy access from any computer within your home network (via your Internet browser)
- With your free EnerGenie.com user account you will get easy worldwide access to your EG-PM1W-001, via internet or the free PowerMan app
- Built-in 300 Mbps WiFi-repeater for improved range of your wireless network

## 1.2. Specifications

- High-speed 300Mbps WiFi 802.11 b/g/n interface
- WLAN repeater mode
- Input voltage: up to 250 VAC, 50 – 60 Hz
- Maximum load current: 16 A

- Maximum power consumption: 2.5 W
- Hardware schedule features:
  - Maximum number of independent hardware schedule events – 45 per socket
  - Time setting accuracy in seconds
  - Combine repeating and one time events
- Timer accuracy: less than 2 seconds error per day provided that power is always present. Otherwise there can be an additional error of up to 2 seconds for each time the device is turned off.
- Indoor use only
- Dimensions: 135 x 92 x 78 mm
- Net weight: 0.35 Kg

### **1.3. Hardware requirements**


- Local area network with WLAN router
- Any Internet-enabled computer connected to the local area network
- Computer running Windows® 2000/XP/7/8 is required for using the *Power Manager* software (use of this software is not compulsory)

### **1.4. Package contents**

- EG-PM1W-001
- User manual and Quick installation guide
- CD with *Power Manager* software for Windows

## 2. Indicators and controls of EG-PM1W-001

Figure # 1



- *ON/OFF switch* – toggles the socket output between on and off
- *ON indicator* – shows a light if the socket is ON, otherwise the socket is OFF.
- *Reset button (pinhole)* – when pressed and held for 5 seconds, the socket's WLAN configuration reverts to its default settings (See default settings list in p.4.5).

### **3. Installation**

- It is strongly recommended to avoid installing the device in damp or wet places.
- EG-PM1W-001 should be connected to the European AC wall socket of the standard DIN 49 440.

#### **3.1. Easy setup of the EG-PM1W-001 with the PowerMan app**

- Connect your EG-PM1W-001 to the power socket and wait around 20 seconds for socket initialization.
- Press the reset button in the pinhole on the front using a blunt narrow pin (e.g paperclip) and keep pressed for 5 seconds to reset the EG-PM1W to the defaults. Wait another 20 seconds for socket initialization.
- Meanwhile download and install the free PowerMan app on your smartphone or tablet PC:



- For iPhone 4 (or higher) :

<https://itunes.apple.com/ru/app/powerman/id486183471>



- For Android OS 2.1.x (or higher):

<https://play.google.com/store/apps/details?id=peacemaker.energeniepowermanager>



- Create your free user account on energenie.com cloud server by following the instructions in the app itself, or sign in to your existing account.
- Add the new EG-PM1W device by following the instructions in the app itself.

### 3.2. Setting up the EG-PM1W-001 as an Access Point (using web browser)

- Connect your EG-PM1W-001 to the power socket and wait around 20 seconds for socket initialization.
- Your EG-PM1W-001 can now be switched on and off by means of the *ON/OFF* switch. If the ON indicator is green, this means that the socket is now live and connected to the power supply.
- Open up a web browser in your WiFi-enabled computer or smartphone.
- To connect to the EG-PM1W-001 WiFi network:
  - Connect to the network with SSID “*EG-PM1W\_XXXXXX*”, where “XXXXXX” is last 6 digits of the EG-PM1W-001 MAC address.
  - No password is needed to connect.
  - Ensure that the option *Get the IP address automatically* is enabled on your PC.
- Go to <http://egsetup.net> (or <http://10.10.10.254>) in your browser.
- Input login “admin”, password “admin” in the login page (see Figure #2) and click *Sign In*. You should now be connected, and able to

manage the EG-PM1W-001 via the web interface. Initially, the EG-PM1W-001 is in “*access point*” mode. If you want to change to “*repeater*” mode follow the steps described in the following section (3.2).

### 3.3. Setting the WiFi repeater mode (using web browser)

- Log into the EG-PM1W-001 web interface, as described in section 3.2.
- Select *Wireless Network* in the left menu (see Figure #3).
- If it is required by the WLAN network configuration, choose *Static IP* for the *Network type* setting and fill in the IP address, mask, gateway, DNS manually, otherwise select the *DHCP Client* option to allow the network to assign the IP address automatically. The *DHCP Client* option is suitable for most users.
- Click *Site survey*.
- In the “*Wireless WAN (Client) Setting*” page select the SSID of your network, and enter your *Passphrase* (see Figure #4).
- In order to ensure that the repeater network is secure, and to allow for seamless roaming between the host and repeater’s network, it is recommended to use the same encryption type and password of the host WLAN network. In this case, leave *Set the AP security with this information* option checked.

- Click “Apply”. At this point, the EG-PM1W-001 should be in WiFi repeater mode. The default SSID is “*EG-PM1W\_XXXXXX*”. You can change the repeater’s SSID to the SSID of your host network, WiFi channel, or encryption type and password in the *Wireless Network* page.

### 3.4. Power Manager software installation for Windows PC

- Before setting up the *Power Manager* software, you need to configure the access to the EG-PM1W-001 web interface (see sections 3.1 - 3.2).
- Insert the *Power Manager* CD into the PC CD-ROM drive and run setup.exe. If your laptop does not have CD-ROM player, just download the latest software from [www.energenie.com](http://www.energenie.com) and run the installer package.
- In order to connect the EG-PM1W-001 with the *Power Manager* software, you need the IP, PM port and PM password settings. You can find the IP in the *Wireless Network* page in the web interface. You can also find the IP by using the *LAN find* utility in the *Power Manager* software. The *PM port* and *PM password* need to be set in advance in the *System* page. Usually the *PM port value* is 5000. The password shall contain between 1 and 8 characters.
- In *Power Manager*, Select *Device->Add device* from the main menu. Enter the device name, IP address, PM port, PM password, and then click OK. After a few seconds, the EG-PM1W-001 icon will

appear in the main window and the connection status will turn green. EG-PM1W-001 is now connected and can be managed. Note, antivirus or firewall software may block connection to the EG-PM1W-001. Please, configure your antivirus/firewall to allow connections to the IP address and port of your EG-PM1W-001.

### **3.5. Setting up the EG-PM1W-001 for use with the EnerGenie.com free user account**

- Log into the EG-PM1W-001 web interface and go to the *Socket* page.
- Click *Register*. The *energenie.com* login page will be opened in a new browser window.
- Click *New account or login to your existing account*. Complete the form in newly opened page. After clicking *Register*, a new page with your EG-PM1W-001 device will appear. Click the device icon to open the device page from where you may control the device.
- Return to the *Socket* page and click *Activate*. Wait a few seconds until the status under the button shows “*Connected and Activated*”. The EG-PM1W-001 can now be managed via your user’s account on *EnerGenie.com*.

## **4. The web server**

Your EG-PM1W-001 is equipped with a web-server which allows managing the device using any web browser such as Internet Explorer, Firefox, Chrome, etc.

#### 4.1. Web-server login

To access the web-server of the EG-PM1W-001, just open Internet Explorer (or other browser) and input <http://egsetup.net> or the IP address of your EG-PM1W-001 (for example *http://192.168.1.241*). The *login* page will then be displayed (see Figure #2).

*Javascript* must be enabled in your Internet Explorer (or other browser) settings.

Figure # 2



The image shows a login form for the Energenie device. At the top is the Energenie logo. Below it are two text input fields: the first is labeled 'Username' and the second is labeled 'Password'. At the bottom of the form is a green button with the text 'Sign in' in white.

The default login is: username: *admin* password: *admin*

It is recommended to change the password on the *System* page after the first login. After successfully logging in, you will arrive at the *Socket* page

## 4.2. Socket

Through the *Socket* page (see Figure #3) you will be able to see the status of your manageable socket and switch the socket on and off manually.


The *system time* shows the time currently set on the device. It is used for the execution of the time schedule.

The *Network* section shows you the current WLAN network settings and status.

The *Socket* page also allows you to set up how the EG-PM1W-001 can be accessed and managed over the internet via *EnerGenie.com* when there is no static external IP address. Through the *EnerGenie.com* interface, it is possible to switch the device on and off, as well as set or check the time schedule. Setting up this free service is described in section.3.4 .

Figure # 3

EnerGenie WLAN Power Management



### Socket Device

**Socket**

Socket 1

Name1

**ON**

Switch OFF

System Time 01.01.1970 3:12:36

**EnerGenie Account**

Activate
Register

Status Not activated

**Network**

Connection Type	DHCP
IP Address	10.10.10.254
Net Mask	255.255.255.0
Mac Address	88:86:27:01:34:3A
AP SSID	EG-PM1W_01343A / OPEN
Destination SSID	/
Status	Disconnected

Copyright © 2009–2014, Gembird Software Ltd.




### 4.3. Power Schedule

On the *Power Schedule* page (see Figure #4) it is possible to set up the time schedule for switching the socket ON or OFF. You can add or remove up to 45 schedule events (use + and – buttons). For each event, you can set the date and time when it occurs and select whether it is executed only once or periodically. The entire schedule can be cleared by clicking the *Clear schedule*.

Although the hardware schedule is saved when the device is powered off, the local time will be reset. Therefore, for proper schedule execution after powering off, selecting the *NTP enable* option is highly recommended (it is enabled by default). Otherwise the local time will need to be restored manually after each “Power Off” event.

Figure # 4

EnerGenie WLAN Power Management



Socket Device

**Power Schedule**

Wireless Network

System

Log Out

### Power Schedule

**New Schedule**

1	ON	13	May	2014	10	48	08	Once	+
2	ON	13	May	2014	10	48	46	Once	-

Loop period:  Days  Hours  Minutes  Seconds

Socket Name:

**Schedule List**

Num	Event	Date/Time	Period	Loop period	Socket Name	Operation
1	ON	13.5.2014 8:46:49	Periodic	1Days	Name1	<input type="button" value="Del"/>
2	OFF	13.5.2014 19:00:00	Periodic	1Days	Name1	<input type="button" value="Del"/>
3	ON	17.5.2014 15:10:00	Once	-	Name1	<input type="button" value="Del"/>

Copyright © 2009–2014, Gembird Software Ltd.

## 4.4. Wireless Network Settings


On the *Wireless Network* page (see Figure #5) you can set up the EG-PM1W-001 IP and WLAN settings. In the *Basic Network* section, you can

choose whether to connect automatically through DHCP or provide a static IP address. In the *Wireless AP* (Access Point) section, you can configure the WLAN network settings assigned to EG-PM1W-001. Newly chosen settings will be implemented after clicking *Apply*.

These settings also work when the device is in *Repeater* mode provided that a connection to the host AP is established. To set up this connection, click *Site survey*. In the new page select the SSID option corresponding to the host AP from the list. You can rescan SSIDs by clicking *Refresh*. The security settings for the repeater should usually be the same as those for the host AP. To copy these settings from the host AP, leave the *Set the AP security with this information* option checked. When selected, input the pass phrase and click *Apply*. The EG-PM1W-001 will connect to that host AP. You will then need to reconnect your client to the EG-PM1W-001 SSID.

Figure # 5

**EnerGenie WLAN Power Management**



- Socket Device
- Power Schedule
- Wireless Network
- System
- Log Out

## Wireless Network Settings

**Basic Network**

Network Type	DHCP Client
--------------	-------------

[Apply](#)

**Wireless AP**

Wireless Name (SSID)	EG-PM1W_013438
Wireless Channel	Channel 4
MAC Address	88 B6 27 01 34 38
Authentication	WPA2PSK AES
Pass Phrase	12345678

**LAN Settings**

IP Address	10.10.10.254
Subnet Mask	255.255.255.0

[Apply](#)

**Wireless WAN (Client)**

Destination SSID	gmb	<a href="#" style="background-color: #e57373; color: white; padding: 2px 10px; border-radius: 3px;">Site Survey</a>
Mac Address	40 16 9f cb 08 2a	
Authentication	WPA2PSK	
Encryption type	AES	
Status	Connected (192.168.1.116)	

Figure # 6

**EnerGenie WLAN Power Management**

- Socket Device
- Power Schedule
- Wireless Network
- System
- Log Out

### Wireless WAN(Client) Setting

**Wireless Connection Information**

Destination SSID:	<input type="text" value="gmb"/>
MAC Address (BSSID)	<input type="text" value="40:16:9f:cb:08:2a"/>
Authentication:	<input type="text" value="WPA2PSK"/>
Encryption type:	<input type="text" value="AES"/>
Pass phrase:	<input type="text" value="12345678"/>
Current Status:	Connected

Set the AP security with this information

**Site Survey List**

SSID	Ch	Security	Mode	Signal	Select
ARCOMI	1	WPA2PSK/AES	11b/g/n	24%	<input type="radio"/>
<b>gmb</b>	4	WPA2PSK/AES	11b/g/n	55%	<input checked="" type="radio"/>
TANUKI_TECH1	6	WPA2PSK/AES	11b/g/n	5%	<input type="radio"/>
Florange	7	WPA1PSK/WPA2PSK/TKIP/AES	11b/g/n	44%	<input type="radio"/>
eridan417	8	WPA/PSK/TKIP/AES	11b/g/n	10%	<input type="radio"/>
partner	11	WEP	11b/g	29%	<input type="radio"/>
newvpi_EXT	11	WPA2PSK/AES	11b/g/n	29%	<input type="radio"/>
newvpi	11	WPA/PSK/AES	11b/g	0%	<input type="radio"/>
	12	WPA1PSK/WPA2PSK/TKIP	11b/g	15%	<input type="radio"/>

Copyright © 2009–2014, Gembird Software Ltd.

## 4.5. System

On the *System* page you can change the socket name, web-server login data, time (set it automatically using the NTP server or manually using the client computer), *Power Manager* interface TCP port and password (for accessing by *Power Manager* software), update the firmware and reset the configuration to the default values (works in the same way as the hardware Reset button).

The socket name should refer to the device which is attached to this socket. For example, if the socket is connected to the TV, then the socket name should be set to “TV”.

Before the EG-PM1W-001 schedule can be set up, the internal clock must be correct. Click *Sync with Client Time* to copy the time from the client computer used to access the web server. Alternatively, if the option *Enable NTP* is set (it is set by default) then the time will be taken from the NTP server. The device will try to connect with the server every 18 hours. The first synchronization takes place in 15 seconds after clicking *Apply*.

For NTP time correction to work properly the device should have access to the Internet and have a proper DNS server setting.

A password may be set to control access to the *Power Manager* software. The password should be between 1 and 8 characters

The *Power Manager* software needs an open port to access the EG-PM1W-001. By default, port 5000 is used, but this can be changed to any other port except for port 80 which is always occupied by the web server.

Don't forget to click *Apply* to save your settings.

Clicking *Load defaults* resets the WLAN configuration settings to the default values.

Default settings:

All time schedules cleared

Network type (in Repeater mode): DHCP client

Wireless Name (SSID): "EG-PM1W\_XXXXXX", where "XXXXXX" are the last 6 digits of the EG-PM1W-001 MAC address.

Wireless Channel: 6

Authentication: NO SECURITY

IP address: 10.10.10.254

Subnet mask: 255.255.255.0

Socket Name: Name1

System time: 1.1.1970 00:00:00

PM port: absent

PM password: absent

Enable NTP: disabled


NTP server: time.nist.gov

Username: admin

Password: admin

Figure # 7

EnerGenie WLAN Power Management



- Socket Device
- Power Schedule
- Wireless Network
- System
- Log Out

## System

### Device Settings

Socket Name	Name1	<a href="#">Change Socket Name</a>
System time	01.01.1970 3:17:42	<a href="#">Sync with Client Time</a>
PM Port	<input type="text" value="5000"/>	
PM Password	<input type="text" value="QWERTY"/>	
Enable NTP	<input checked="" type="checkbox"/>	
NTP server	<input type="text" value="time.nist.gov"/>	ex: time.nist.gov ntp0.broad.mit.edu time.windows.com

[Apply](#)

### Web server account

Username	<input type="text"/>	<a href="#" style="background-color: #0070c0; color: white; padding: 5px 15px; border-radius: 3px;">Apply</a>
Password	<input type="text"/>	

### Firmware & Configuration

Version	EG-PM1W 1.0.3 ( 08:45 2014/05/14 )	
Firmware File	<input type="text"/>	<a href="#">Browse...</a>

[Load Defaults](#)
[Firmware Upload](#)

Copyright © 2009–2014, Gembird Software Ltd.



## 4.7. Web-server logout

Having finished working with EG-PM1W-001, choose *Log Out* in the main menu. If you don't do this, you will be logged out automatically after 6 minutes of inactivity. While you are logged into the web server, it can be accessed from any other computer. In the meantime the *Power Manager* software can still access the EG-PM1W-001.


## 5. EnerGenie.com device interface

With your free personal account from *EnerGenie.com* you will be able to access your EG-PM1W-001 from anywhere in the world using any internet-enabled device (desktop PC, laptop, smartphone etc). See section 3.4 on how to register your EG-PM1W-001 on the server and set up the connection.

### 5.1. Logging in

To login into your *EnerGenie.com* account just open the webpage [www.energenie.com/user](http://www.energenie.com/user) in your internet browser and enter your login and password in the login window (see Figure #8).

Figure # 8



The image shows a login form with the following elements:

- A label "Login" positioned to the left of a text input field.
- A label "Password" positioned to the left of a second text input field.
- A label "Remember me" followed by a small square checkbox.
- A green button labeled "Login" located to the right of the "Remember me" checkbox.
- Two green buttons at the bottom: "New account" on the left and "Forgot Password" on the right.

Check *Remember me* for automatic login in the future (the website will then save a cookie on your computer). If you lose your password, click the *Forgot Password* button.

## 5.2. Device management page

After a successful login you will see the list of your registered devices and their corresponding sockets.

Figure # 9

## EG-PM1W



Last seen online: 15-May-2014 22:17:24  
 IP: 85.113.223.23  
 MAC: 88-B6-27-01-34-3A  
 Device web-interface: [192.168.1.112](http://192.168.1.112)

Refresh

Socket1

ON



Delete device

This page will automatically update itself and will show you the time when your device was last seen online (the last time the device communicated with the server) and the status of each socket.

Click your device name to change the device name.

Click the socket name to change it and show the time schedule on socket. You can also set the time schedule from here.

Click the *On/Off* buttons to switch the socket on or off. Note that these actions can only be properly executed if the device is switched on, connected to the internet and activated.

The *Last seen online* status information lets you check if the device keeps communicating with the server.

## **6. Power Manager software**

The *Power Manager* software is designed to support not only EG-PM1W-001 but also other power management family products (please visit [www.energenie.com](http://www.energenie.com)).

Figure # 10



## 6.1. Managing EG-PM1W-001

Install the *Power Manager* software and follow the instructions in section 3.3 to connect the EG-PM1W-001.


Click the socket icon in the device list window (see Figure #10). A device control panel will appear (see Figure #11).

Figure # 11



The panel will show the status of each socket (green for on, red for off). Each socket can be toggled on or off by double-clicking on it. Clicking on the *Settings* button will display the *Settings* dialog box (see Figure #12).

Figure # 12




- The device and socket can be renamed (for example Printer or Scanner) by clicking *Rename*.
- Check the *System tray* checkbox if you want to put the icon of the socket into the system tray. You can choose the icon from drop down list box. This icon will provide a fast method for controlling the device connected to the socket, such as switching it on or off or checking the status.
- You can also assign a hot key to switch the socket on/off. Check *Switch ON* and/or *Switch OFF* and specify the hot keys
- To switch the socket on/off on Windows startup (wake up), check *On Windows startup* and choose the required action
- To switch the socket on/off on Windows shutdown (sleep), check *On Windows shutdown* and choose the required action

## 6.2. Setting up the hardware schedule

Using the *Hardware schedule* button available from the *Settings* window you can create the hardware timer schedule (see Figure #13). To add a new record, click the *Add* button.

Figure # 13





- In the window which appears, specify the required time and the action.


Figure # 14

The screenshot shows a dialog box titled "Add entry". It contains the following elements:

- Title Bar:** "Add entry" with a close button (X).
- Section Header:** "Entry" (highlighted with a green border).
- Time:** A time spinner set to "14:30:00" and a date dropdown menu set to "21.05.2014".
- Action:** A dropdown menu set to "Switch OFF" and a radio button labeled "Periodic".
- Buttons:** "OK" and "Cancel" buttons at the bottom.

- To edit the record, select it and click the *Edit* button or just double click on the entry (see Figure #13). An *Edit entry* window will appear
- To remove the record, select it and click *Remove* (see Figure #13). You can select multiple entries using the Ctrl and Shift keys. You can also remove all entries from the schedule by clicking *Clear* (see Figure #13)
- To repeat your event (for example if you want to perform the same events every day) Click *Loop*, (see Figure #13) and specify the loop time period in the *Edit loop period* window (see Figure #15).

Figure # 15



- After the schedule record has been created, click *Apply* (see Figure #13) to save the hardware timer schedule changes. Any incorrect entries will be highlighted and an error message will appear. After correcting all the errors, click *Apply* again.
- Click *Sync* (see Figure #13) to synchronize the device timer with the PC's internal clock. Note that after synchronization, any past entries will be removed from the schedule.

The above actions can also be performed through the pop-up menu which appears when you right-click over the event line in the table (see Figure #13).

The hardware schedule keeps running even when the device is powered off. However it is not recommended to leave the device powered off for longer than 1 week, as the built-in battery might become discharged. In this


case the internal clock of the device would be reset and as result some schedule events would not be executed. The sockets would also forget their previous status (they will be switched on). Leave the device switched on for one day to fully charge the battery.

### 6.3. Setting up software schedule

Clicking *Software schedule* in the the Settings window you can create the software timer schedule (see Figure #16).


The software timer schedule will only be executed if the managing computer is on and the *Power Manager* is launched.

Figure # 16



- To add a new task, click the *Add* button. The *Add task* window will appear (see Figure #17)

Figure # 17



In the *Add task* window, check *Switch ON time* and/or *Switch OFF time* and specify the time to switch the socket on and/or off. If you want the same event to be performed periodically, check *Perform task every*

and specify the time interval. You can also add remarks about the task in the *Comment* field. To enable or disable the task, check or uncheck *Enabled*.

- To edit the task, select it (see Figure #16) and click the *Edit* button or just double click on the task. The *Edit task* window will appear (see Figure #18)

Figure # 18

The screenshot shows a dialog box titled "Edit task" with a close button in the top right corner. The dialog is divided into several sections:

- Task:** This section contains two rows of settings, each with a checked checkbox, a text field, a time dropdown, and a date dropdown.
  - Row 1:  Switch ON time: 22:00, 21.05.2014
  - Row 2:  Switch OFF time: 23:00, 21.05.2014
- Perform task every:** A checked checkbox followed by a text field containing "1" and a dropdown menu set to "days".
- Comment:** A text input field.
- Enabled:** A checked checkbox.

At the bottom of the dialog are two buttons: "OK" and "Cancel".

- To remove the task, select it and click *Remove* (see Figure #16). You may select multiple tasks using Ctrl and Shift keys. You can also remove all tasks by clicking *Clear*.


The above actions can also be performed through the pop-up menu which appears when you right-click over a task in the table (see Figure #13).

#### 6.4. Setting up application events

Using the *Application events* window you can specify the socket events when a certain application is launched or closed. You can also associate switching the sockets off or on with the placement and removal of particular files in certain folders.


To use this feature, click *Application events* under *Settings* (Figure #12). The following window will appear (see Figure #19).

Figure # 19



- To add a new program event, click *Add app*. The *Add program event* dialog will appear (see Figure #20).

Figure # 20



Specify the application title and path to it using the Browse (...) button or by manually entering the Title and Path name fields. If you use the Browse (...) button you can also select a shortcut to the application. In this case the application title and path name will be taken automatically via the shortcut if possible. After you have specified the application, check *On run* and/or *On exit* and choose the event (switch on or off).




The *On run* event will take place when the first window of the selected application is opened. The *On exit* event will take place when the last window of the application is closed.

Setting up application events in this way allows your device to operate as an advanced standby-killer. For example, your scanner can be switched on or off whenever Photoshop is started or closed.

- To add a new file event, click *Add folder* (see Figure #19). The *Add file event* window will appear (see Figure #21).

Figure # 21



Specify the path to the folder you would like to monitor using the Browse (...) button or typing it manually in the *Path name* field. The wild card characters \* and ? can be used to select a group of files. Check *On placing* and/or *On removal* and select the event and delay.

The *On placing* event will take place when the first file matching the specified file name is placed into the specified folder. The *On removal* event will take place when the last file matching the specified file name is removed from the specified folder.

Setting up file events in this way allows your device to operate as an advanced standby-killer. For example, your printer can be turned on before printing and turned off after printing by checking whether there are any files in the print queue. Use the *Add folder* button to assign c:\windows\system32\spool\printers folder to switch your printer on whenever you start printing and to switch it off again afterwards.

If you have several printers connected to the same computer, we suggest moving the default spool directory of each printer to a separate location.

- To edit the event, select it and click *Edit*, or just double click on the event (see Figure #20). The *Edit file event* window will appear (see Figure #22)

Figure # 22

**Edit file event**

Event

Title:

Path name:  ...

File name:  \*.\*

On placing:   Delay on placing:

On removal:   Delay on removal:

Enabled

OK Cancel

- To remove the event, select it and click *Remove* (see Figure #20). You can select multiple events using Ctrl and Shift keys. You can also remove all events by clicking the *Clear* button.

The above actions can also be performed through the pop-up menu which appears when you right-click over an event in the table (see Figure #19).

## 7. Managing EG-PM1W-001 via your own software

To let you switch the sockets on or off from your own applications the following command line interface syntax is supported:

- `pm.exe -[on | off] -device name -socket name`
- Examples:
- `"C:\Program Files\Power Manager\pm.exe" -on -My EnerGenie -Socket1`
- `"E:\Utils\PM3\pm.exe" -off -My EnerGenie -Table lamp`
- Execute `pm.exe` with `-info` key (`pm.exe -info`) to get the complete information about the status of the current devices.

For each of the connected devices, the following information will then be provided and placed into `Info.ini` file in the *Power Manager* folder:

- `DeviceName=<the user specified device name>`
- `Socket#name=< the socket name specified by the user>`
- `Socket#SwitchState=<TRUE/FALSE>`, where `TRUE` is when the socket is switched on, or `FALSE` is when the socket is switched off

Example: "C:\Program Files\Power Manager\pm.exe" - info

Each use of this command line option totally overrides the data in Info.ini file.

In order to use these commands, *Power Manager* must have already been launched.

## 8. EG-PM1W-001 SDK

For advanced users we offer a software development kit (SDK) to manage the device. For more information, please check the SDK manual in the SDK folder on the supplied CD, or download the latest SDK from [www.energenie.com](http://www.energenie.com).

## **9. GNU General Public License - Copyright Notice and Warranty Disclaimer**

The product's firmware contains free software; you can redistribute the free software and/or modify it under the terms of the GNU General Public License as published by the Free Software Foundation (version 2 of the License).



The free software is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE.

All copyrights are identified in more detail in the free software source code. The free software source code can be at least for a period of three years be requested from Gembird Europe B.V. (mail to: [postmaster@gmb.nl](mailto:postmaster@gmb.nl)) or write to: Wittevrouwen 56, 1358 CD, Almere Haven, The Netherlands)

You should have received a copy of the GNU General Public License along with this program; if not, write to the Free Software Foundation, Inc., 51 Franklin Street, Fifth Floor, Boston, MA 02110-1301, USA.

This product is tested and complies with the essential requirements of the laws of member states concerning R&TTE(1999/5/EC). The CE declaration can be found under [www.gembird.eu](http://www.gembird.eu)

Dieses Produkt wurde getestet und stimmt mit den grundlegenden Anforderungen der Richtlinie EMC(2004/108/EC) überein. Die Konformitätserklärung kann auf unserer Webseite [www.gembird.de](http://www.gembird.de) heruntergeladen werden



**Waste disposal:**


Do not deposit this equipment with the household waste. Improper disposal can harm both the environment and human health. For information about waste collection facilities for used electrical and electronic devices, please contact your city council or an authorized company for the disposal of electrical and electronic equipment.

**Entsorgungshinweise:**


Werfen Sie dieses Gerät nicht in den Hausmüll. Unsachgemäße Entsorgung kann sowohl der Umwelt als auch der menschlichen Gesundheit schaden. Informationen zu Sammelstellen für Altgeräte erhalten Sie bei Ihrer Stadtverwaltung oder einer autorisierten Stelle für die Entsorgung von Elektro- und Elektronikgeräten.

**Richtlijnen m.b.t. afvalverwerking**


Batterijen en accu's dienen als kleinchemisch afval afgeleverd te worden bij toegewezen afvalverzamelpunten (zie [www.afvalgids.nl](http://www.afvalgids.nl)). U dient ervoor te zorgen dat de batterijen/accu's leeg zijn en dus geen stroom meer kunnen leveren. Let op, de batterijen/accu's dienen onbeschadigd ingeleverd te worden.

Gooi dit product niet weg in uw vuilnisbak. Dit kan zowel het milieu als de menselijke gezondheid schade toebrengen. Informatie over het inleveren van dit product kunt u inwinnen bij uw gemeentelijke vuilnisdienst of andere geautoriseerde instelling in uw buurt.





**Traitement des déchets:**




Ne jetez pas cet appareil dans les déchets domestiques. Un traitement inapproprié peut être dommageable à l'environnement et à la santé humain.

Vous trouvez des informations sur les centres de rassemblement des appareils vieux chez l'administration municipale ou

chez un centre autorisé pour le traitement des appareils électriques ou électroniques.



<b>WARRANTY CONDITIONS</b> 	<b>GARANTIE BEDINGUNGEN</b>   
<p>The receipt must clearly list the date of purchase and the part number, in addition it should be printed. Keep the receipt for the entire warranty period since it is required for all warranty claims. During the warranty period the defective items will be credited, repaired or replaced at the manufacturer's expense. Work carried out under the warranty neither extends the warranty period nor starts a new warranty period. The manufacturer reserves the right to void any warranty claim for damages or defects due to misuse, abuse or external impact (falling down, impact, ingress of water, dust, contamination or break). Wearing parts (e.g. rechargeable batteries) are excluded from the warranty. Upon receipt of the RMA goods, Gembird Europe B.V. reserves the right to choose between replacement of defective goods or issuing a credit note. The credit note amount will always be calculated on the basis of the current market value of the defective products</p>	<p>Das Kaufdatum und der Gerätetyp sind durch eine maschinell erstellte Kaufquittung zu belegen. Bitte bewahren Sie Ihren Kaufbeleg daher für die Dauer der Garantie auf, da er Voraussetzung für eine eventuelle Reklamation ist. Innerhalb der Garantiezeit werden alle Mängel, wahlweise durch den Hersteller entweder durch Instandsetzung, Austausch mangelhafter Teile oder im Austausch, behoben. Die Ausführung der Garantieleistung bewirkt weder eine Verlängerung noch einen Neubeginn der Garantiezeit. Eine Garantieleistung entfällt für Schäden oder Mängel die durch unsachgemäße Handhabung oder durch äußere Einwirkung (Sturz, Schlag, Wasser, Staub, Verschmutzung oder Bruch) herbeigeführt wurden. Verschleißteile (z.B. Akkus) sind von der Garantie ausgenommen.</p>
<p>Gembird Europe B.V.                  Wittevrouwen 56, 1358CD Almere                  The Netherlands  <a href="http://www.gembird.nl/support">www.gembird.nl/support</a>  <a href="mailto:support@gmb.nl">support@gmb.nl</a>                  Tel. +31-36-5211588</p>	<p>GEMBIRD Deutschland GmbH                  Coesterweg 45, 59494 Soest                  Deutschland  <a href="http://www.gembird.de/support">www.gembird.de/support</a>  <a href="mailto:support@gembird.de">support@gembird.de</a>                  Tel. +49-180 5-436247                  0,14 € pro Minute aus dem deutschen Festnetz.                  Mobilfunkpreise können abweichen</p>

<b>GARANTIE VOORWAARDEN</b>   	<b>CONDITIONS DE GARANTIE</b>   
<p>Op de aankoopbon moeten de aankoopdatum en productomschrijving duidelijk vermeld staan.</p> <p>Gelieve de aankoopbon de gehele garantieperiode te bewaren, deze is ten alle tijden benodigd voor alle garantie aanspraken. Tijdens de garantieperiode zullen alle gebreken verholpen of vervangen worden door de fabrikant d.m.v. reparatie, omruiling van het defecte onderdeel of het gehele apparaat. Aanspraken tijdens de garantieperiode leiden niet tot verlenging hiervan. Garantieaanspraak vervalt bij schade of gebreken die ontstaan zijn door oneigenlijk gebruik, misbruik of invloeden van buitenaf (vallen, stoten, water, stof, vuil of breken). Slijtagegevoelige onderdelen (b.v. batterijen) zijn uitgesloten van garantie. Bij ontvangst van de RMA goederen behoudt Gembird zich het recht om te kiezen tussen vervanging van de defecte waren of het uitgeven van een kreditnota. Het bedrag van de kreditnota zal altijd gecalculeerd zijn op basis van de huidige marktprijs voor het defecte produkt.</p>	<p>Le talon de garantie doit énumérer clairement la date d'achat et le type d'appareil.</p> <p>Conservez le reçu d'achat pendant toute la durée de la garantie car elle est nécessaire pour toute réclamation.</p> <p>Au cours de la période de garantie tous les défauts doivent être remplacé aux frais du fabricant, soit par la réparation ou le remplacement de la pièce défectueuse ou l'ensemble du produit.</p> <p>Les travaux effectués sous garantie ne prolongent pas la période de garantie ni ne commencent pas une nouvelle période de garantie.</p> <p>Le fabricant se réserve le droit d'annuler toute demande de garantie pour les dommages ou défauts dus à une mauvaise utilisation, abus ou les effets externes (chute, choc, pénétration de l'eau, la poussière, etc..).</p> <p>Les pièces d'usure (par exemple les piles rechargeables) sont exclus de la garantie.</p> <p>Dès réception de la marchandise sous garantie, le SAV de Gembird Europe BV se réserve le droit de choisir entre le remplacement des produits défectueux ou de délivrer un avoir.</p> <p>Le montant d'avoir sera toujours calculée sur la base de la valeur actuelle du marché des produits défectueux.</p>
<p>Gembird Europe B.V.                  Wittevrouwen 56, 1358CD Almere                  The Netherlands  <a href="http://www.gembird.nl/support">www.gembird.nl/support</a>  <a href="mailto:support@gmb.nl">support@gmb.nl</a>                  Tel. +31-36-5211588                  € 0,15 p/m binnen Nederland                  Exclusief mobiele telefoonkosten</p>	<p>Gembird Europe B.V.                  Wittevrouwen 56                  1358CD Almere, The Netherlands  <a href="http://www.gembird.nl/support">www.gembird.nl/support</a>  <a href="mailto:support@gmb.nl">support@gmb.nl</a>                  +33(0) 251 404849                  Prix d'appel depuis telephone fixe Pays-Bas : 0.15 euro / min                  Prix d'appel depuis telephone mobile / autre pays - selon                  operateur</p>

<b>ГАРАНТИЙНЫЙ ТАЛОН</b> 	<b>УМОВИ ГАРАНТІЙНОГО ОБСЛУГОВУВАННЯ</b> 
<p>1. Гарантийное обслуживание предоставляется в течение срока гарантии, при наличии правильно и четко заполненного гарантийного талона, и изделия в полной комплектации. Серийный номер и модель изделия должны соответствовать указанным в гарантийном талоне.</p> <p>2. Гарантийное обслуживание представляет собой бесплатное устранение всех неполадок (ремонт), или замену изделия на новое (аналогичное).</p> <p>3. Гарантия не распространяется на неисправности, вызванные следующими причинами:</p> <ul style="list-style-type: none"> <li>• использование изделия не по назначению.</li> <li>• нарушение условий эксплуатации, хранения или перевозки изделия, которые указаны в настоящей инструкции.</li> <li>• подключение нестандартных или неисправных периферийных устройств, аксессуаров.</li> <li>• механические повреждения, попадание внутрь изделия посторонних предметов, веществ, жидкостей, насекомых.</li> <li>• ремонт изделия не уполномоченными на то лицами.</li> </ul> <p>4. Комплектность и внешний вид изделия проверяются Покупателем при получении товара в присутствии персонала фирмы.</p> <p>Послепродажные претензии по укомплектованности и внешнему виду не принимаются.</p> <p>Наименование изделия: _____</p> <p>Модель _____</p> <p>Серийный номер _____</p> <p>Срок гарантии _____</p> <p>Дата продажи « ____ » _____ 20 ____ года</p> <p>Фирма-продавец: _____</p> <p>Адрес и телефон фирмы-продавца: _____</p> <p>М.П. С условиями гарантии ознакомлен и согласен:</p> <p>Продавец: _____ Покупатель: _____</p>	<p>1. Гарантійне обслуговування надається протягом терміну гарантії, при наявності Гарантійного талону, заповненого належним чином, та виробу в повній комплектації.</p> <p>2. Гарантійне обслуговування не підтримується в разі порушення правил експлуатації, зберігання або перевезення виробу, що зазначені в інструкції по експлуатації виробу.</p> <p>3. Гарантійне обслуговування скасовується у випадках:</p> <ul style="list-style-type: none"> <li>- наявності механічних пошкоджень або слідів стороннього втручання;</li> <li>- пошкодження викликані стихійним лихом або нещасним випадком, включаючи й блискавку, потраплянням у виріб сторонніх предметів, рідин, комах, тощо;</li> <li>- пошкодження викликані застосуванням або підключенням нестандартних або несправних периферійних пристроїв, аксесуарів;</li> </ul> <p>4. Гарантія не поширюється на витратні матеріали та додаткові аксесуари;</p> <p>3 гарантійними умовами згоден.</p> <p>Підпис покупця: _____</p> <p>ГАРАНТІЙНИЙ ТАЛОН № _____</p> <p>Товар/модель _____</p> <p>Серійний номер _____</p> <p>Термін гарантії _____</p> <p>Дата продажу _____</p> <p>Продавець (назва, телефон) _____</p> <p>Печатка та підпис продавця _____</p> <p>3 гарантійних питань звертайтеся до сервісних центрів Gembird. Про адреси та контакти Ви можете дізнатися на сайті <a href="http://www.gembird.ua">www.gembird.ua</a> або по телефону 044-4510213.</p>